

PINTEK

4 Digits, 2 Display, 2 Output 100 VA DC Power Supply

Features:

- 4 Digits, 2 Display
- Low Ripple & Noise: $<0.3 \text{ mVrms}$
- High Resolution Read Out: $10\text{mV}/1\text{mA}$
- 10 Turn VR for Voltage and Current Setting
- Dual Output: $0 \sim 30\text{V}/0 \sim 3\text{A}$; $5\text{V Fixed}/0 \sim 3\text{A}$



PW-4032



BP-253

- 18awg, 2000V, 80°C
- UL 1803 Standard E56290
- Max Load = 10 Amps, $L = 100\text{cm}$
- Ship with self-retractable plug cable for safe and convenient use.

Pintek Electronic Co., Ltd
www.pintek.com.tw

PW-4032 100 VA DC Power Supply



SPECIFICATIONS

Power Transformer:	E.I. Type Transformer
Max. Continual Output Power:	105VA
Max. Raised Temperature:	< 40° C
Independent Output:	0~30V/0~3A, 5V Fixed / 0~3A; Dual Output
Constant Voltage Characteristic	
Load Regulation:	± 0.01% + 10mV
Line Regulation:	± 0.01% + 5mV
Ripple & Noise:	< 0.4mVrms
Constant Current Characteristic	
Load Regulation:	< 15mA
Line Regulation:	± 0.01% + 2mA
Ripple & Noise:	< 2.5mArms
5V Fixed Output	
Regulation:	Line Regulation < 5mV, Load Regulation < 10mV
Ripple & Noise:	< 1.5mVrms
Voltage Accuracy:	5V ± 0.25V
Max. Output Current:	3A
Display	
Voltage:	4 Digits 0.36" Green LED
Current:	4 Digits 0.36" Red LED
Accuracy:	0.05% + 3 digits
General	
Power Source:	ACV 115/230 ± 10%, 50/60Hz
Dimensions(W x H x D):	230 x 170 x 310 mm
Weight:	6.8 kg

PINTEK

Pintek Electronic Co., Ltd

2F No.32 Tai-Pen Rd., Shulin City, Taipei Hsien, Taiwan
 Tel: 886-2-86859562~3 Fax: 886-2-86852081
<http://www.pintek.com.tw>
 E-Mail : pintek@pintek.com.tw ; pintek@ms26.hinet.net

SALES AGENT